



Li-36 Battery Upgrade
Installation-Approved
for Consolidated Fiber Service

For any PSI questions, please call
270 350-9020

480 Reasonover Drive
Franklin, KY 42134
P: (270) 813-1110
E: info@powertecsolutions.net

INSTALLATION OF BATTERY MODULE FOR 8 HOURS

1. Locate the power supply installed by Consolidated Communications in your home. It is 6in x 3.5in unit mounted to a wall or set on a desktop.
2. Unplug the AC from the wall.
3. Push up on the power supply to remove from wall plate. The wall plate and power supply slide apart.
4. Slide new battery module on to the wall plate by sliding it down on the wall plate.
5. Slide power supply on to the battery module.
6. Plug the AC power back into the wall.



BATTERY MODULE REPLACEMENT AND RECYCLE

1. When top light labeled "Battery" is red then battery module needs to be replaced.
2. Follow above instructions on Installation of battery module for 8 hours.
3. Inside the shipment there will be a shipping return label and instructions to send used battery module back to PSI for recycling.

INSTALLATION OF BATTERY MODULE FOR 24 HOURS

1. Locate the power supply installed by Consolidated Communications in your home. It is 6in x 3.5in unit mounted to a wall or set on a desktop.
2. Unplug the AC from the wall.
3. Push up on the power supply to remove from wall plate. The wall plate and power supply slide apart.
4. Mount 3 place wall plate to a wall near AC power in the place of original single place plate. Mount so that connector pins are facing up.
5. Slide down all three batteries on to the plate.
6. Slide power supply on the left side of the plate on top of one of the batteries.
7. Slide cover down to lock on battery cover plate.
8. Plug AC back into the wall.

